
Data Sheet

RE-Series - Valve Regulated Lead Acid Battery RE5-12

SPECIFICATIONS		
Nominal voltage	12	V
20-hr rate Capacity to 1.75VPC at 20°C	5	Ah
10-hr rate Capacity to 1.75VPC at 20°C	4.6	Ah
DIMENSIONS	1.0	741
Length	90 (±0.5)	mm
Width	70 (±0.5)	mm
Height	102 (±0.5)	mm
(height over terminals)	106 (±0.5)	mm
Mass (typical)	1.96	kg
TERMINAL TYPE	1.00	
FASTON (Quickfit / release)	6.35	mm
OPERATING TEMPERATURE RANGE	0.00	111111
	0000 +	- · CO0C
Storage	-20°C to +60°C -15°C to +50°C	
Charge	-15°C to +50°C -20°C to +60°C	
Discharge STORAGE	-20°C to	U +0U-C
Capacity loss per month at 20°C (approx)	3	%
CASE MATERIAL		/0
Standard - Flame Retardant	ARC (II	II 04:1/0)
	ABS (UL94:V0)	
Option	ABS (UL94:HB)	
CHARGE VOLTAGE	10.05 (.10/)	V
Float charge voltage at 20°C	13.65 (±1%) 2.275 (±1%)	V/cell
Float Charge voltage temperature correction factor	-3	mV/cell/°C
(for variations from the standard 20°C)		
Cyclic (or Boost) charge at 20°C	14.5 (±3%) 2.42 (±3%)	V V/cell
Cyclic Charge voltage temperature correction factor (for variations from the standard 20°C)	-4	mV/cell/°C
CHARGE CURRENT		
Float charge current limit	No limit	Α
Cyclic (or Boost) charge current limit	1.25	Α
MAXIMUM DISCHARGE CURRENT		
1 second	120	Α
1 minute	40	Α
SHORT-CIRCUIT CURRENT & INTERNAL RESISTANCE		
(according to EN IEC 60896-21)		
Internal resistance	N/A	mΩ
Short-Circuit current	N/A	А
IMPEDANCE		
Measured at 1 kHz	42	mΩ
PERFORMANCE & CHARACTERISTICS		
Refer to the technical manual	RE	
DESIGN LIFE		
EUROBAT Classification: General purpose	6 to 9	years
Yuasa design life @ 20°C	up to 10	years
Yuasa design lile @ 20°C	αρ το το	yoars

PELIART WHITE HOURS LAND AND ARTHUR RES-12 3V 50Ah Manusus H with the control of the control



3RD PARTY CERTIFICATIONS

ISO 9001 - Quality Management Systems
ISO 14001 - Environmental Management Systems
EN 18001 - OHSAS Management Systems
UNDERWRITERS LABORATORIES Inc.



STANDARDS

IEC61056







ALL DATA IS SUBJECT TO CHANGE WITHOUT NOTICE Issue No.: V.1 / Issue Date: July 2010



YUASA BATTEHY SALES UK LTD. Unit 13, Hunts Rise South Marston Industrial Estate Swindon SNI3 ATG

Installation

Can be installed and operated in any orientation except permanently inverted

Handles

Batteries must not be suspended by their handles (where fitted)

vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

Gas Release

VRLA Batteries release hydrogen gas which can form explosive mixtures in air. Do not place inside a sealed container

Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations